
Project: LIVERMORE, CA 94550 page: 1 of 2


Date: 5/18/2011 Engineer: XXX

# **DOMINATOR 2100 BOILER SEISMIC ANCHORAGE (ASCE 7-05)**


## **Slab on Grade Applications Only**

## **Equipment Parameters:**





## Seismic Parameters:



$$\begin{array}{c|c} R_p = & \textbf{2.500} \\ F_a = & \textbf{1.000} \end{array} \text{ (Default value for Anchorage per ASCE 7-05 Table 13.6-1)} \\ S_{MS} = F_a {}^*S_s = & \textbf{1.798} \\ S_{DS} = 2/3 {}^*S_{MS} = & \textbf{1.199} \end{array} \text{ (ASCE 7-05 Eqn. 11.4-3)} \\ \end{array}$$

Seismic Design Category = **D** 

# Seismic Force:

$$F_p = (0.4^*a_p{}^*S_{DS}{}^*W_p)/(R_p/I_p) = \begin{tabular}{c} $200.4$ & LBS. (ASCE 7-05 Eqn. 13.3-1) \\ Upper Limit: $F_{pMAX} = 1.6^*S_{DS}{}^*I_p{}^*W_p = \begin{tabular}{c} $2004.2$ & LBS. (ASCE 7-05 Eqn. 13.3-2) \\ LBS. (ASCE 7-05 Eqn. 13.3-2) \\ LBS. (ASCE 7-05 Eqn. 13.3-3) \\ LBS. (ASCE 7-05 Eqn. 13.3-1) \\ LBS. (ASCE 7-05 Eqn. 13.3-1) \\ LBS. (ASCE 7-05 Eqn. 13.3-1) \\ LBS. (ASCE 7-05 Eqn. 13.3-2) \\ LBS. (ASCE 7-05 Eqn. 13.3-2) \\ LBS. (ASCE 7-05 Eqn. 13.3-2) \\ LBS. (ASCE 7-05 Eqn. 13.3-3) \\ LBS. (ASCE 7-05 Eqn. 13.3$$

Project: LIVERMORE, CA 94550

Date: 5/18/2011 Engineer: XXX


# **DOMINATOR 2100 BOILER SEISMIC ANCHORAGE (ASCE 7-05)**

#### **Design Anchorage Force:**

Horizontal Shear Force Per Anchor:

$$R_H = F_p/4 =$$
 **93.9** LBS.

# Overturning Resistance About Point A:



$$x = 29.31$$
 in.  $x = lesser of L or W$ 

2 of 2

page:

$$M_{OT} = F_p^* cg =$$
 **536.7** LBS.-FT.

$$M_{RES} = W_p^* x/2 =$$
 1276.3 LBS.-FT. OK, No Uplift

Vertical Acceleration: assume  $\rho = 1.0$ 

Ev = 
$$\rho^* Fp + 0.2^* S_{DS}^* W =$$
 344.5 LBS. (ASCE Section 13.3.1)

$$R_{VNETUP} = (M_{OT}/(2*x))-(W_p/4)+(Ev/4) =$$
 LBS. No Uplfit

## Force Summary Per Corner:

#### Component Anchorage:

$$R_{HNET} =$$
 93.9 LBS.  $R_{VNETUP} =$  0.0 LBS.

## Anchors Embedded in Concrete or CMU:

$$1.3*R_p*R_{HNET} =$$
 305.3 LBS.   
  $1.3*R_p*R_{VNETUP} =$  0.0 LBS.